ImageWriter

Microchip PIC12F508Device Support Detail & Setup

ImageWriter Support Hierarchy

Manufacturer: Microchip

Device: PIC12F508

Objects for PIC12F508

Flow Object Name:	*Program / Execute*	*Verify*	*Load*	*Object Size (Words)*
FLASH	●	●	●	0x200soheil
OSCCAL	●	●	●	0x01
USER ID	●	●	●	0x04
CONFIG[1]	●	●	●	0x01
ERASE[2]	●			
ERASE ALL[2]	●			
p_MCT10F[3]	●		●	0x04

[1] See support note 3
[2] ERASE restores the OSCCAL bits, ERASE ALL does not. See support note 4 for more info.
[3] Default Clock Speed = 500KHz

Physical Layer Connector Setup for PIC12F508 High Voltage Method

ImageWriter:		Target:
Connector Pin #	***Pin Name***	***Connections***
1	GND	GND
2	GND	GND
3	TXD (MOSI/TDO)	See note 1
4	RXD (MISO/TDI)	ISCPDAT
5	RTS (TMS)	NOCONN
6	CTS	NOCONN
7	XCLK	ISCPCLK
8	RST	NOCONN
9	SCL	NOCONN
10	SDA	NOCONN
11	GND	GND
12	GND	GND
13	VPP/EXT_IN	13.0V DC
14	VPP/EXT_OUT	MCLR
15*	Target V+ (7.0V max)	Supply 4.5-5.5 V
16*	Target V+ (7.0V max)	Supply 4.5-5.5 V
17	GND	GND
18	GND	GND
19	ImageWriter Power	Supply 9-24 VDC
20	ImageWriter Power	Supply 9-24 VDC

[1] Pin 3 must be connect to Pin 4 with an external 1K Ohm resistor in series.
*Maximum Pin-Driver output voltage = 4.2V.

Support Notes:

1. Data verification does not occur automatically during program. Include a Verify operation in your flow to ensure data integrity (highly recommended).
2. OSCCAL is separated into a separate object to prevent accidental changes. This word is normally mapped in the device as the last byte in the "Flash" space. See Microchip documentation for more information on the OSCCAL word
3. Config bit mapping is per manufacturer data-sheet. All bits stored in ImageWriter memory must be properly set.
4. "ERASE" object will erase the device and then restore the OSCCAL / Backup OSCCAL values. An Erase operation failure indicates OSCCAL / Backup OSCCAL restoration was not successful.

Disclaimer

Typical implementation of **ImageWriter** includes but is not limited to external power provision to **ImageWriter**, device access restrictions on the target board, external hardware on the target board, or software changes created by the user affecting timing, device erasure, programming, or verification. Data I/O warranty coverage applies only when the product is used in conformance with technical specifications put forth by Data I/O and by the semiconductor device manufacturer.

In the interest of achieving the highest levels of safety and quality, Data I/O recommends that all programming processes be tested and documented in a prototype project prior to transition to volume manufacturing. For additional information see In-System Programming Design Guidelines (http://www.dataio.com/isp).

ImageWriter programs semiconductor devices through the use of circuits designed precisely to operate in accordance with specifications outlined by the device manufacturer. Provision and calibration of power supplies are critical for proper operation. **ImageWriter** has been fully tested by Data I/O Corporation for quality performance.