ImageWriter

Microchip PIC16F73 Device Support Detail & Setup

ImageWriter Support Hierarchy

Manufacturer: Microchip

Device: PIC16F73

Objects for PIC16F73

Flow Object Name:	*Program / Execute*	*Verify*	*Load*	*Object Size (Words)*
FLASH	●	●	●	0x800
USER ID	●	●	●	0x04
CONFIG	●	●	●	0x01
DEVICE ID			●	0x01
ERASE ALL	●			
p_MCT16F[1]	●		●	0x08

[1] Default Clock Speed = 500KHz

Physical Layer Connector Setup for PIC16F73:

ImageWriter:		Target:
Connector Pin #	***Pin Name***	***Connections***
1	GND	GND
2	GND	GND
3[1]	TXD (MOSI/TDO)	See note 1
4[1]	RXD (MISO/TDI)	RB7
5	RTS (TMS)	NOCONN
6	CTS	NOCONN
7	XCLK	RB6
8	RST	NOCONN
9	SCL	NOCONN
10	SDA	NOCONN
11	GND	GND
12	GND	GND
13	VPP/EXT_IN	Supply 12.75 – 13.25 V
14	VPP/EXT_OUT	MCLR/VPP
15*	Target V+	*Supply 4.75-5.25 V
16*	Target V+	*Supply 4.75-5.25 V
17	GND	GND
18	GND	GND
19	Pod Power	Supply 9-24 VDC
20	Pod Power	Supply 9-24 VDC

[1] Pin 3 must be connect to Pin 4 with an external 1K Ohm resistor in series.
*Maximum Pin-Driver output voltage = 4.2V.
*See Support Note #2 for V Target+ and VCC requirements.

Support Notes:

1. Data verification does not occur automatically during program. Include a Flash Verify operation in your flow to ensure data integrity (highly recommended).
2. Microchip specifies that erase and programming operations must be performed with VCC between 4.75 and 5.25 V DC. However, VCC during verify operations can be between 2.0 and 5.5V and must be set at your boards actual operating voltage.

3. If reprogramming a previously programmed device, be sure to Erase ALL prior to programming. This will erase the FLASH, Config Word, and the 4-word User ID.
4. The Configuration Word is mapped per Microchip's device spec.

Disclaimer

Typical implementation of **ImageWriter** includes but is not limited to external power provision to **ImageWriter**, device access restrictions on the target board, external hardware on the target board, or software changes created by the user affecting timing, device erasure, programming, or verification. Data I/O warranty coverage applies only when the product is used in conformance with technical specifications put forth by Data I/O and by the semiconductor device manufacturer.

In the interest of achieving the highest levels of safety and quality, Data I/O recommends that all programming processes be tested and documented in a prototype project prior to transition to volume manufacturing. For additional information see In-System Programming Design Guidelines (http://www.dataio.com/isp).

ImageWriter programs semiconductor devices through the use of circuits designed precisely to operate in accordance with specifications outlined by the device manufacturer. Provision and calibration of power supplies are critical for proper operation. **ImageWriter** has been fully tested by Data I/O Corporation for quality performance.