ImageWriter

Atmel AT24C164 Device Support Detail & Setup

ImageWriter Support Hierarchy

Manufacturer: Atmel

Device: AT24C164

Objects for AT24C164

Flow Object Name:	*Program / Execute*	*Verify*	*Load*	*Object Size (Bytes)*
EE	●	●	●	0x800
P_I2C[1]	●		●	0x8

[1] Default I2C Clock Frequency = 400KHz, Default I2C Bus Address = 000.

Physical Layer Connector Setup for AT24C164

ImageWriter:		Target:
Connector Pin #	***Pin Name***	***Connections***
1	GND	GND
2	GND	GND
3	TXD (MOSI/TDO)	NOCONN
4	RXD (MISO/TDI)	NOCONN
5	RTS (TMS)	NOCONN
6	CTS	NOCONN
7	XCLK	NOCONN
8	RST	NOCONN
9	SCL	SCL
10	SDA	SDA
11	GND	GND
12	GND	GND
13	VPP/EXT_IN	NOCONN
14	VPP/EXT_OUT	NOCONN
15*	Target V+ (7.0V max)	Supply 1.8-5.5 V
16*	Target V+ (7.0V max)	Supply 1.8-5.5 V
17	GND	GND
18	GND	GND
19	ImageWriter Power	Supply 9-24 VDC
20	ImageWriter Power	Supply 9-24 VDC

*Maximum Pin-Driver output voltage = 4.2V.

Support Notes:

1. I2C connection must have pull-up resistors provided. If your target board does not provide pull-ups, ImageWriter can be configured to do so. See your integration guide on how to change the ImageWriter I2C pull-up resistors.
2. A post-programming EE Verify operation is highly recommended to ensure data integrity.
3. I2C Bus Address value should be set to match levels on A0, A1, A2 pins. Use the p_I2C object to change the I2C Bus Address. Default Bus_Address is 000.

Disclaimer

Typical implementation of **ImageWriter** includes but is not limited to external power provision to **ImageWriter**, device access restrictions on the target board, external hardware on the target board, or software changes created by the user affecting timing, device erasure, programming, or verification. Data I/O warranty coverage applies only when the product is used in conformance with technical specifications put forth by Data I/O and by the semiconductor device manufacturer.

In the interest of achieving the highest levels of safety and quality, Data I/O recommends that all programming processes be tested and documented in a prototype project prior to transition to volume manufacturing. For additional information see In-System Programming Design Guidelines (http://www.dataio.com/isp).

ImageWriter programs semiconductor devices through the use of circuits designed precisely to operate in accordance with specifications outlined by the device manufacturer. Provision and calibration of power supplies are critical for proper operation. **ImageWriter** has been fully tested by Data I/O Corporation for quality performance.